

## AX-FIR3053-RE-IT

Industrial automation components

|                       |                                  |
|-----------------------|----------------------------------|
| <b>Manufacturer</b>   | Omron                            |
| <b>Catalog number</b> | ax-fir3053-re-it                 |
| <b>Category</b>       | Industrial automation components |
| <b>Product type</b>   | Industrial automation components |
| <b>Status</b>         | Active product                   |

### Technical specification

|                               |  |
|-------------------------------|--|
| <b>Display Name</b>           | AX-FIR3053-RE-IT   |
| <b>Description</b>            | RX footprint RFI filter, 53A, 400VAC, 3-phase, for 15 to 22 kW models, IT installation |
| <b>ETIM Class</b>             | EC002025   |
| <b>EAN</b>                    | 4547648876506.0  |
| <b>Group</b>                  | EA   |
| <b>Fam</b>                    | EAZ  |
| <b>Country of Origin</b>      | GBR  |
| <b>Tariff Code</b>            | 8529909790.0   |
| <b>OC Code</b>                | AA030347E  |
| <b>Second Item Number</b>     | AXFIR3053REIT  |
| <b>Category</b>               | Falownik - Akcesoria   |
| <b>Stat Fam</b>               | 5YYE   |
| <b>Stat Fam description</b>   | EMC filters  |
| <b>Publication sort</b>       | 2DAM2  |
| <b>Primary Package Length</b> | 501  |
| <b>Primary Package Width</b>  | 275  |
| <b>Primary Package Depth</b>  | 90   |
| <b>Dimensions</b>             | 501mm x 275mm x 90mm   |
| <b>Primary Package Weight</b> | 4436 g   |

### Description

RX footprint RFI filter, 53A, 400VAC, 3-phase, for 15 to 22 kW models, IT installation