

## MDX60B0005-5A3-4-00

Industrial automation components

|                       |                                  |
|-----------------------|----------------------------------|
| <b>Manufacturer</b>   | Sew-Eurodrive                    |
| <b>Catalog number</b> | mdx60b0005-5a3-4-00              |
| <b>Category</b>       | Industrial automation components |
| <b>Product type</b>   | Industrial automation components |
| <b>Status</b>         | Active product                   |

### Technical specification

|                             |             |
|-----------------------------|-------------|
| <b>Current</b>              | 1.8 A       |
| <b>Relay Specifications</b> | 500 VAC     |
| <b>Voltage</b>              | 380 - 500 V |
| <b>Power</b>                | 0.55 kW     |
| <b>Frequency</b>            | 50 - 60 Hz  |
| <b>Horsepower</b>           | 0.55 KW     |
| <b>Cooling Capacity</b>     | 0.55 kW     |
| <b>Product Type</b>         | Inverter    |
| <b>Signal Type</b>          | 500         |
| <b>Signal Level</b>         | 500 V       |

### Description

The SEW EURODRIVE MDX60B0005-5A3-4-00 inverter is designed to operate within a voltage range of 380 to 500 V. It offers a current of 1.8 A and a power output of 0.55 kW, making it an ideal solution for applications requiring efficient energy management. The operating frequency ranges from 50 to 60 Hz, and its cooling efficiency is also 0.55 kW. The product features a signal type of 500 and a signal level of 500, ensuring stable and reliable operation.